

SPY-NVR4POE4K/SPY-NVR4POE4KND SPY-NVR8POE4K/SPY-NVR8POE4KND



Tips: For user manual and future firmware updates, please go to https://metrahometheater.com/spyclops-surveillance-systems.html for download.

Fast Networking

Step: Right click mouse in main menu→fast networking→Choose Auto Config →Click OK

If want to manual config, input IP address, click diagnose. If NVR shows healthy network, make sure the connection to the network is good.



IPC Set UP

2.IPC Set UP

Step: Right click mouse→Click Video Manage→Click Refresh to search IPC \rightarrow Two ways to add IPC

(1) Click the IPC searched, then click add, IPC will add to target channel

(2) Click Auto add(Auto add can add all the IPC searched to channel list)

Delete channel: Delete channel information Edit channel: Manually revise channel parameters (such as password of user name) Click OK to finish operation.

🔍 Colit coroop	Video Manage							
- spiit screen	21	Protocal	default		IPC chan	nel is upd	ating	
S Video Manage		ID.	Device name	IP a	ddress	Port	Protocal	
e man manage		41.	TEXAM	192.14	98.66.11	-000	81	TROTTERT
🗇 System setup		42	IPCAM	192 10	58 66 12	80	NI	Additions
		43	IPCAM	192 10	58.66.13	- 80	N 1	Auto And
🖽 Video plavback		44	LPCAM	192 10	58 66 15	-80	NI	
in the of play babit		CP AF	TROAM	102 10	01 00 00	108	NI	
📳 Video backun		40.	TPCAM	192.10	58.66.21	80	N I	
		48	TPCAM	192.1	58.66.22	80	N1	
🔇 Color adjust		< 6 /	11 >					
• DT3 · I		Added de	vice:		Remai	ning device: 15		
PIZ control		Channel	Device name	If address		Status		Ī
			IPCAM	192.168	3.66.12	Conne	ct success	Destruction
🖞 Manual record		4			-	No vi	ino source	. umique al
		3					leo source	- Minima Inte
Volume		4				No vic	leo source	homelese
						No Vic	leo source	-
🚱 Setup Wizard		7				No vic		
		8				No video source		
🎲 Fast network		< 1 /	2 >	Remia	ining netw	ork bandy	vidthi: 75Mbpa	
🕛 Exit System								
							UK I	Cancel

3 Video Detection

(1)

Step 1: Right click mouse \rightarrow System setup \rightarrow Channel setup \rightarrow choose Video detection \rightarrow choose motion \rightarrow click Enable \rightarrow Click OK.

Step 2: Right click mouse→System setup→Record setup→Record plan→choose motion→choose all→click Copy to→click OK to save setting.



4 Video Playback

Steps: Right click→Video playback→choose date, channel, record mode-click search-then you can view playback file.

Warm prompt:

- 1. Illustration for playback button: K rewind; K playback previous seconds: ▶ playback following seconds; ▶ play: ■ pause: ▶ fast forward x2,x4,x8
- 2. Play file: Choose the recording file in file list, as number "1" shown in picture. Choose one of the recording, click "play" to play to recording file;

3. Video backup: Choose the recording file in file list, as number "1" shown in picture. Insert a thumb drive, click "video backup" to backup the file;

4. Timeline: click "date" and "time" at left bottom to check the timeline of recording, show number "2" shown in picture;

on the timeline with recording file, left click the mouse, then can playback the file.

🖁 Split screen 🕨 🕨	2017/01/1
🛚 Video Manage	
} System setup	ATT
Video playback	
] Video backup	
Color adjust	2017/01/1
) PTZ control	
) Manual record	
0 Volume 🕨	
• Setup Wizard	-
Fast network	2 Day



5 Video Backup

① Exit System

Steps: Right click mouse→Video backup→choose channel No.

→choose Record mode→In search time, input beginning time and end time \rightarrow click search, recording will show \rightarrow choose the video that needs to be backed up →click video backup.

Tips: Support 32G U disk backup maximum, recording file will be packed every one hour

🏥 Split screen 🕨									
🤜 Video Manage								v 12	
🕼 System setup	Record	mode	Mani	🗸 Manual 🗸 Time 🗸 Motion 🗸 Sens					
🎞 Video playback 🕨	Search time		2015/	08/27	00 :00 - 2	3:59	Search		
🕮 Video backup	ID	Channe	Mode	Begin time	End time	Duration	Size	Select	
T and a state of the state of the		16	Time	20:30:18	21011041	00:41:29	128		
🔇 Color adjust	- 2-	15	Time	20:30:18	21:11:41	00:41:23	13M		
O PT7 control	3	14	Time	20:30:18	21:11:41	00:41:23	12M		
	4	13	Time	20:30:18	21:11:41	00:41:23	12M		
👌 Manual record	5	12	Time	20:30:18	21:11:41	00:41:23	12M		
🗆 Volume 🕨	6	11	Time	20:30:18	21:11:41	00:41:23	12M		
	7	10	Time	20:30:18	21:11:41	00:41:23	13M		
o ^e Setup Wizard	8	9	Time	20:30:18	21:11:41	00:41:23	12M		
🚯 Fast network	K 1	/7	>	USB storag	e 🔽 🚺	Backup	Can	cel	
① Exit System									



Step 1: Fast Networking \rightarrow check the IP address of the device

Step 2: Access the computer in same LAN, input video recorder's IP address and port (if port is 80, no need to input) in IE browser or any other browser. Then it will access in LAN log in web page, input user name and password, click Login



Step 3: Once access is successful, you can reach the video

Tips: Please make sure NVR and computer are in the same network segment



7 Access In WAN

Step 1: Right click mouse→Fast Networking→check the ID of the device



Step 2: Open the IE browser, enter the www.e-seenet.com in the address bar. Then it will access log in web page, input ID, user name and password, click login





Tips: Video quality depends on the upload speed of the NVR and download speed of computer. Each channel needs above 30KB.

Mobile application download and installation

Search for "SPYCLOPS" on Apple APP Store or Google Play Store





iPhone APP

Google play APP

0

PTZ

Playback

5

8

40A

MetraHomeTheater.com 866-839-9187

460 Walker Street Holly Hill, FL 32117-2653 ©2017 Metra Electronics Corporation Designed and Manufactured to Metra Home Theater Group Specifications MADE IN CHINA

Step 1: Register Step 2: Enter device interface Step 3: Add device Step 4: Added successfully. Click channel No.to get video Step 5: Remote playback



SPYCLOPS